

HT-2000P

YFAST YSAFE YRELIABLE



■ DIELECTRIC WITHSTAND/GROUND CONTINUITY 2000 VAC with offline test time/current limit setup and viewing.

FEATURES

- AC Output to 2000 volts; delivers up to 20mA.
- Logic controlled, one button test. LED's indicate test progress. Upon failure, buzzer sounds and testing is terminated.
- Output voltage, leakage current limit, voltage ramp-up time and test duration are controlled from the rear panel. Leakage current limit and test time are displayed on LED and are adjustable with high voltage output defeated.
- Ground continuity test is defeatable for testing of two wire products.
- Nema 5-15R receptacle provided on front panel for high voltage output.
- Automatic voltage rampdown circuit eliminates residual voltage.

- Operation instructions provided on the rear panel.
- Performs to UL and CSA safety agency requirements for production hipot testing.
- Can be connected to our GF-30ac Ground Bond tester for complete TUV and European safety testing.
- Ergonomically designed for safety, speed and efficiency.
- Small footprint and light weight.
- ▶ Economical, durable and compact.
- Calibration Certificate included.
- ▶ Test leads included.
- ▶ TEST-LINK Compatible



The blue box that tests. And tests.



The Right Source For Your Test & Measurement Needs

2222 Verus Street Suite C San Diego CA 92154 USA
Toll Free: 866.363.6634 Tel: 619.429.4545 Fax: 619.374.7012
Email: sales@calright.com http://www.calright.com

HT-2000P









ELECTRICAL

Output: 0-2000 Volts AC +0 -10% into NEMA 5-15R receptacle mounted on front panel

Pigtail and Receptacle adapters available for most configurations.

Leakage Current 1-20 mA set using LED display with HV output defeated. (See picture on right above for

leakage current display.)

Pass/Fail Criteria:

Duty Cycle:

Ground Continuity: 3 ohm ± 5% * (defeatable)

Leakage Current: User adjustable 1-20 mA in 0.1 mA increments

Dielectric Breakdown: True arc detection using separate high frequency transformer.

Test Time: User adjustable 1-60 sec. in 1 second increments using LED display with HV output

defeated. (See center picture above for test time display)

Voltage Ramp Time: User adjustable .5-5 sec.

Test Status: Progress Lights on Front Panel show test progress and results.

100%

Meter Accuracy: ±2%: 500V to 2000V

Discharge Time: Immediate voltage discharge upon failure or end of test.

Test Adjustments: Tamper-proof operation available by pulling knobs.

Calibration Certificate good for one year, User's Manual, return lead



ENVIRONMENTAL

Operating Temperature:: 15-40°C

Relative Humidity Range: 0-90% non-condensing



GENERAL >

Included with tester:

Input Power Requirements: 114-127 volts, 50/60 Hz

Weight: 10.5 lbs.

Dimensions: 9.250 (W) x 4.250 (H) x 10.000 (L) in.



SAFETY >

Transformer Output: <500 VA

Visual Indication Of Voltage Output: Provided by front panel meter, directly connected to high

voltage output.

Failure Indication: Audible, provided by internal buzzer

Visual, provided by red LED's on front panel Test automatically terminated on failure.

Ground Test: Provided; 3 ohm pass/fail point. May be defeated for testing of products

with two wire power supply cords.

Leakage Test: Provided; 5mA factory set pass/fail point, user adjustable.

Operation Instructions: Provided on rear panel.

The blue box that tests. And tests.

