

# The Right Source. The Right Solutions.



### AC LEAKAGE CURRENT TESTER

## TECHNICAL DATA

#### **FEATURES**

- 10µA resolution
- Large 3-3/4 (4000-count) LCD
- Shielded transformer jaws open to 1.2"
- Max/Min and Data hold
- Overload protection
- Auto power-off
- Supplied with TL-88-1 test leads, AM-4 "AAA" batteries and C-820 soft carrying case

#### **SPECIFICATIONS**

Current Range: 40mA to 100A AC Resolution: 10µA to 100mA AC Accuracy: ±(1.0% +3 digits) Voltage Range: 400 VAC Resolution: 0.1 VAC

Accuracy:  $\pm (1.5\% + 10 \text{ digits})$ Resistance Range: 40 to  $400\Omega$ 

**Resolution**:  $0.1\Omega$ 

Accuracy:  $\pm(1.0\% + 2 \text{ digits})$ 

Continuity Test:  $40\Omega$  threshold, beeper at 2.5kHz

Dimensions: 209 x 43 x 30mm

Weight: 200g

#### **ORDERING INFORMATION**

ST-9809	AC Leakge Current Tester
FC-300	Fused Test Lead Set
CERTICM1	NIST Calibration Certificate
ST-9809-NIST	Current Tester & NIST



